AirTap Warm-air Hand Dryer 372

IR sensor Wall-mounted Stainless Steel with satin finish 2-year warranty

DAN DRYER AirTap features a minimalist, modern design in stainless steel with satin finish. The intelligent temperature control technology detects the room temperature and adjusts the heating element.

Application

DAN DRYER AirTap is a powerful hand dryer suitable for toilet rooms with a high visitor frequency. With its elegant slim design, the hand dryer is the perfect choice for toilet rooms with a behind-mirror solution. The DAN DRYER Tap range is an ideal build-in solution for construction projects and automatic hand wash stations.

Technical data

	DAN DRYER AirTap
	Prod. No.: 372
	Touch-less warm-air hand
Туре	dryer with IR sensor
Dimensions tap	H 50 x W 50 x D 220 mm
Dimensions motor	H 203 x W 306 X D 150 mm
Tube length	300-320 mm
Material	Stainless steel, satin finish
Drying cycle	10-15 sec.
Connection	230 V, 50/60 Hz, Klasse 👍
Total wattage	600-1000 W
Heating element	100-500 W
Motor	500 W
Noice level	68.5-70.5 dBA
Max. air capacity	84-101 m/sec.
Max. Air outlet temperature	57° C
Net weight	5.6 kg
IP rating	IP35

Tender text

Touch-less hand dryer in stainless steel with satin finish for wall mounting. Infra-red sensor and electronic timer, drying cycle: 10-15 sec. IP35, 230 V, 50/60 Hz, 1000 W, Class I (earthed). 68.5-70.5 dBA. Net weight: 5.6 kg. H: 38 mm, W: 50 mm, D: 220 mm.

Approval

UL, CE, GS, BSMI, EMC, LVD, WEEE and RoHS CE ROHS



References

Shopping centres, restaurants, hotels, airports, sports facilities, schools and public institutions.

Standard colour

Stainless steel, satin finish

Activation

Infrared sensor and electronic timer. Touchfree. Activation distance adjustable between 20 - 130 mm. Automatic stop after 60 seconds of continuous use.

Motor type

Commutator motor with carbon brushes. 22,000-29,000 revolutions/min.

Protection

Automatic thermal cut-out in both motor and heating element.

Installation

Machine intended for wall mounting. Connection to fixed installation or via circuitbreaker. Installation must be carried out by a qualified electrician.





